







KEY FEATURES

- · Self-powered point source system.
- · 2-channel Class D amplifier, 1200Wrms.
- · 96kHz FIR processing.
- · Control, monitoring, and EQ via IP through ALMA™.
- ·1 x 12" (12GX3N4C) + Compression driver, 3" VCD (M78N)
- · Latest generation transducers with Neodymium.
- · 70° x 40° (H x V) dispersion, rotatable horn

DESCRIPTION

The ARA-P12.74 is a point source system that combines technical innovation with acoustic precision. This model is equipped with a single 12", delivering a broad frequency range from 63 Hz to 17 kHz. Its rotatable horn provides a horizontal coverage of 70° and vertical coverage of 40°, ensuring the ARA-P12.74 offers uniform sound dispersion, perfectly suited for medium to long throw applications in various settings.

Powered by a robust class D amplifier with universal mains switching power supply, the ARA-P12.74 provides a continuous power rating of 1200 W, with peak capabilities reaching 2400 W (1600 W for low frequencies and 800 W for high frequencies). The system achieves a maximum linear SPL of 134 dB and a peak SPL of 140 dB, ensuring its powerful performance in any environment.

The advanced electronics of the ARA-P12.74 include a 96kHz sampling rate complemented by an intuitive ALMA control interface for precise sound management. Each unit features a unique processing input channel operating at 96kHz with 10 EQ points and a total delay of 823ms, equivalent to 283 meters, enhancing its adaptability in system setup. The power module's DSP platform is equipped with specially designed Finite Impulse Response filters (FIR) for acoustically flat magnitude and phase response, facilitating a coherent combination with other units of the ARA series, such as the LARA / SARA line arrays.

At the core of the ARA-P12.74 are our custom-engineered 12G3XN4C transducers, specifically designed for this model, featuring a neodymium magnet and a 3-inch Voice Coil Diameter (VCD) for high efficiency, extensive displacement capabilities, and minimal distortion. Complementing the transducers is the M78N compression driver, identical to those utilized in the ARA series line arrays, known for its ability to produce crisp, clear high frequencies. This combination of the 12G3XN4C transducer and the M78N compression driver ensures that the ARA-P12.74 delivers an audio experience that is both powerfully resonant and richly detailed, setting a new benchmark in point source system sound clarity and quality.

Designed with versatility in mind, the ARA-P12.74 is equipped with M10 rigging points, accommodating a wide array of accessories. This adaptability renders it an ideal fit for a variety of venues, configurations and uses.



SPECIFICATIONS

Performance

Frequency Range (-10 dB)	63Hz - 18 kHz
Horizontal Coverage (-6 dB)	70°
Vertical Coverage	40°
Maximum Linear SPL ¹	134 dB
Maximum SPL ²	140 dB

^{1.} Measured Maximum Linear SPL at 1m according to AES75 standard using 18dB crest factor M-Noise.

2. Measured Maximum SPL at 1m using burst noise.

Electronics and Connectors


Nominal Amplifier Power (continuous)	1200 W
Nominal Amplifier Power LF (continuous)	800 W
Nominal Amplifier Power LF (peak)	1600 W
Nominal Amplifier Power HF (continuous)	400 W
Nominal Amplifier Power HF (peak)	800 W
Input Type	Balanced Analog
Input Impeadance	20 kohms
Input Sensitivity	6.2 V (+18 dBu)
Audio Signal Input Connector	1 x Female XLR
Audio Signal Loop Thru Connector	1 x Male XLR
Audio/Data Input Connector	etherCON
Control	ALMA
Audio + Data Loop Thru Connector	etherCON
AC Output Connector	powerCON TRUE1




Current Draw 230 V / 115 V	1.8 A/3.6 A	
Sampling Rate	96kHz	
Enclosure		
Enclosure Construction	Birch Plywood	
Enclosure Geometry	Trapezoidal 10°	
Rigging	M10 Rigging Points	
Finish	ISO-flex Paint	
Color	Black	
IP Rating	IP43	
Dimensions (H x W x D)	690 x 335 x 425 mm 27,0 x 13,0 x 16,8 in	
Net Weight	24,0 kg (54,0 lb)	
Components		
LF Driver	12GX3N4C	
HF Driver	M-78N	


DIMENSIONS











ORDERING INFORMATION

Model	Description	P/N
System		
ARA-P12.74		10420503
Replacement Parts	S	
12GX3N4C	Cone Transducer	20209080
GM-12GX3N4C	Recone Kit	20209090
GM-M75N	Diaphragm	20205080
M-78N	Compression Driver	20208860
Accessories		
ANL-2	Rigging Accessories	10101020
AX-SPG1	Installation & Stacking Acc.	10105050
AX-SPG2	Installation & Stacking Acc.	10105060
AXC-AT	Installation & Stacking Acc.	10104310



AXC-ZT Installation & Stacking Acc. 10104320 AXC-ZT3 Installation & Stacking Acc. 10104327 AXF-X10 Installation & Stacking Acc. 10104833 AXR-AR5 Installation & Stacking Acc. 10104870 AXU-AP12 Installation & Stacking Acc. 10105000 EC-09 Electronic Accessories 20502110 EC-20 Electronic Accessories 20502130 ECPK-20 Electronic Accessories 20502180 ECPK-5 Electronic Accessories 20502100 FC-ARAP12 Transport Accessories 10116120 JP-AP1228 Rigging Accessories 10102964 MATRIX-22 Ara Series 11106140 PLINK1-09 Electronic Accessories 20502150 PP-4 Ara Series 11106150 TRD-2-PACK Installation & Stacking Acc. 10104470 TRD-6 Installation & Stacking Acc. 10104471	AXC-ATSPG	Installation & Stacking Acc.	10105150
AXF-X10	AXC-ZT	Installation & Stacking Acc.	10104320
AXR-AR5 Installation & Stacking Acc. 10104870 AXU-AP12 Installation & Stacking Acc. 10105000 EC-09 Electronic Accessories 20502110 EC-20 Electronic Accessories 20502130 ECPK-20 Electronic Accessories 20502180 ECPK-5 Electronic Accessories 20502100 FC-ARAP12 Transport Accessories 10116120 JP-AP1228 Rigging Accessories 10102964 MATRIX-22 Ara Series 11106140 PLINK1-09 Electronic Accessories 20502150 PP-4 Ara Series 11106150 TRD-2-PACK Installation & Stacking Acc. 10104012 TRD-6 Installation & Stacking Acc. 10104470	AXC-ZT3	Installation & Stacking Acc.	10104327
AXU-AP12 Installation & Stacking Acc. 10105000 EC-09 Electronic Accessories 20502110 EC-20 Electronic Accessories 20502130 ECPK-20 Electronic Accessories 20502180 ECPK-5 Electronic Accessories 20502100 FC-ARAP12 Transport Accessories 10116120 JP-AP1228 Rigging Accessories 10102964 MATRIX-22 Ara Series 11106140 PLINK1-09 Electronic Accessories 20502150 PP-4 Ara Series 11106150 TRD-2-PACK Installation & Stacking Acc. 10104012 TRD-6 Installation & Stacking Acc. 10104470	AXF-X10	Installation & Stacking Acc.	10104833
EC-09 Electronic Accessories 20502110 EC-20 Electronic Accessories 20502130 ECPK-20 Electronic Accessories 20502180 ECPK-5 Electronic Accessories 20502100 FC-ARAP12 Transport Accessories 10116120 JP-AP1228 Rigging Accessories 10102964 MATRIX-22 Ara Series 11106140 PLINK1-09 Electronic Accessories 20502150 PP-4 Ara Series 11106150 TRD-2-PACK Installation & Stacking Acc. 10104012 TRD-6 Installation & Stacking Acc. 10104470	AXR-AR5	Installation & Stacking Acc.	10104870
EC-20 Electronic Accessories 20502130 ECPK-20 Electronic Accessories 20502180 ECPK-5 Electronic Accessories 20502100 FC-ARAP12 Transport Accessories 10116120 JP-AP1228 Rigging Accessories 10102964 MATRIX-22 Ara Series 11106140 PLINK1-09 Electronic Accessories 20502150 PP-4 Ara Series 11106150 TRD-2-PACK Installation & Stacking Acc. 10104012 TRD-6 Installation & Stacking Acc. 10104470	AXU-AP12	Installation & Stacking Acc.	10105000
ECPK-20Electronic Accessories20502180ECPK-5Electronic Accessories20502100FC-ARAP12Transport Accessories10116120JP-AP1228Rigging Accessories10102964MATRIX-22Ara Series11106140PLINK1-09Electronic Accessories20502150PP-4Ara Series11106150TRD-2-PACKInstallation & Stacking Acc.10104012TRD-6Installation & Stacking Acc.10104470	EC-09	Electronic Accessories	20502110
ECPK-5Electronic Accessories20502100FC-ARAP12Transport Accessories10116120JP-AP1228Rigging Accessories10102964MATRIX-22Ara Series11106140PLINK1-09Electronic Accessories20502150PP-4Ara Series11106150TRD-2-PACKInstallation & Stacking Acc.10104012TRD-6Installation & Stacking Acc.10104470	EC-20	Electronic Accessories	20502130
FC-ARAP12Transport Accessories10116120JP-AP1228Rigging Accessories10102964MATRIX-22Ara Series11106140PLINK1-09Electronic Accessories20502150PP-4Ara Series11106150TRD-2-PACKInstallation & Stacking Acc.10104012TRD-6Installation & Stacking Acc.10104470	ECPK-20	Electronic Accessories	20502180
JP-AP1228 Rigging Accessories 10102964 MATRIX-22 Ara Series 11106140 PLINK1-09 Electronic Accessories 20502150 PP-4 Ara Series 11106150 TRD-2-PACK Installation & Stacking Acc. 10104012 TRD-6 Installation & Stacking Acc. 10104470	ECPK-5	Electronic Accessories	20502100
MATRIX-22 Ara Series 11106140 PLINK1-09 Electronic Accessories 20502150 PP-4 Ara Series 11106150 TRD-2-PACK Installation & Stacking Acc. 10104012 TRD-6 Installation & Stacking Acc. 10104470	FC-ARAP12	Transport Accessories	10116120
PLINK1-09Electronic Accessories20502150PP-4Ara Series11106150TRD-2-PACKInstallation & Stacking Acc.10104012TRD-6Installation & Stacking Acc.10104470	JP-AP1228	Rigging Accessories	10102964
PP-4 Ara Series 11106150 TRD-2-PACK Installation & Stacking Acc. 10104012 TRD-6 Installation & Stacking Acc. 10104470	MATRIX-22	Ara Series	11106140
TRD-2-PACK Installation & Stacking Acc. 10104012 TRD-6 Installation & Stacking Acc. 10104470	PLINK1-09	Electronic Accessories	20502150
TRD-6 Installation & Stacking Acc. 10104470	PP-4	Ara Series	11106150
·	TRD-2-PACK	Installation & Stacking Acc.	10104012
TRD-7 Installation & Stacking Acc. 10104471	TRD-6	Installation & Stacking Acc.	10104470
	TRD-7	Installation & Stacking Acc.	10104471

